

MRM-RMS Manual Pull Stations



Description

The MRM-RMS series manual pull station is a high quality non-toxic die cast station manufactured entirely in the USA.

The low profile design and smooth edges offer an attractive yet highly reliable design.

All components are prepainted or have plated surfaces to inhibit corrosion or scratching. Electrically, the MRM-RMS manual stations are equipped with a 10 Amp snap action switch offered in many contact arrangements including gold contacts.

The MRM-RMS stations can be used with or without a break glass rod with replacement requiring no special tool. The break glass rod helps deter nuisance false alarms.

Features

- UL Listed
- Low Profile Design
- Terminal or Pigtail Connection
- 10 Amp SPST, SPDT or DPDT Contacts
- Gold Contacts Available
- Single or Double Action
- Operates with or without a Break Glass Rod
- Allen Wrench or Key Lock/Reset
- Institutional Type Station Available, Needs a Key to Activate and Reset an Alarm
- Durable Non-Toxic Die Cast Aluminum
- Plated Metal Surfaces to Inhibit Corrosion
- Pre-Finished Components, Red is Standard
- Special Colors and/or Finishes Available
- Surface or Semi-Flush Mounting
- LED Option (Red, Green, Yellow)
- Special Silk Screening Available on the Dual Action Cover, "Lift & Pull for Halon Release", "Tornado", "Emergency", etc.



S6491

Technical Data

Electrical Specifications

Switch
10 A, 120 VAC
Gold Contact
1.0 A, 120 VAC
Key Switch
0.5 A, 30 VDC
Phone Jack
0.1 A, 24 VDC

Dimensions

Station
3.2"W x 4.75"H x 0.875"D
DAH Option
3.325"W x 4.75"H x 1.625"D
LP/LPH Option
3.325"W x 4.75"H x 1.625"D

Weight

Station
15.5 oz (420 g)
DAH Option
1 lb 9 oz (756 g)
LP/LPH Option
1 lb 4 oz (560 g)

Mounting

Single Gang Box

Ordering Information

Model	Description
MRM-RMS-1P	Single Action Metal Pull Station, SPST, Pigtail Connections
MRM-RMS-1T	Single Action Metal Pull Station, SPST, Terminal Connections
MRM-RMS-2T	Single Action Metal Pull Station, SPDT, Terminal Connections
MRM-RMS-6T	Single Action Metal Pull Station, DPDT, Terminal Connections
Options	Description
KL	Key Lock/Reset, CAT 120 key
LP	Lift and Pull, Dual Action.
WP	Weatherproof adapter, comes assembled with back box
NYC	New York City Stripe added to the Dual Action Cover
LED	Light Emitting Diode (Red, Green, Yellow)
GCS	Gold Contact, SPST
GCD	Gold Contact, SPDT
PJ	Phone Jack for Fireman Telephone Headsets
INST	Institutional front panel, comes with a key assembly which activates the pull station, NO Pull Handle
PS	Pre-signal Key Switch
EXP	Explosion Proof
Accessories	Description
MRM-DAH	Break Glass Adapter (dual action)
MRM-BB	Surface Mounting Back Box
MRM-FP	Flush Trim Plate